

Notification—Added Functions for the R-09 (Ver. 1.20)

This product has been upgraded to version 1.20.
The following functions have been added with this upgrade.


Repair Files (Repair)

A file repair feature has been added. It repairs files that cannot be played because an accident occurred during recording; for example, an adaptor was mistakenly unplugged or a card was removed.

When the R-09 detects a damaged file, the "Repair" Menu is shown in the finder.

1. Select a song or folder from the <Finder Screen>.

Use the [PLAY Button ▲] and [STOP Button ▼] to select a song or folder, then press the [REC Button].




2. Choose "Repair."

Use the [PLAY Button ▲] and [STOP Button ▼] to select "Repair," then press the [REC Button].

MEMO

This menu is displayed only when the R-09 detects a damaged song.



3. Press the [REC Button] to repair the file.

A confirmation screen is shown. Press the [REC Button] to repair the file.



MEMO

To cancel, press the [FINDER/MENU Button] before pressing the [REC Button].




NOTE

Do not turn off the power while the repair takes place.

4. Return to <Main Screen>.

Press the [FINDER/MENU Button].



NOTE

Even if repaired, up to five seconds at the end of the file may be deleted. Also, this feature cannot repair all files. Do not turn off the power or remove the memory card while using the R-09.

Additional Settings

The following parameters have been newly added to the [Menu Screen].

Category	Menu/Effect	Value (Default value in bold)
Recorder Setup	Max File Size Sets a limit on the size of the file generated during recording. Use this to prevent long MP3 recordings from becoming too large to be read by some software, after the data has been converted to WAV. When the song being recording reaches the specified size limit, the R-09 closes that file and continues the recording in a new file.	64MB/128MB/256MB/512MB/ 1GB/ 2GB
	Peak Hold Sets peak hold for the Level Meter. When peak hold is ON, the highest value for the input signal is held and displayed for a set period.	OFF (no peak hold) ON (use peak hold)
Display Setup	Rec/Peak LED Links the [REC Indicator] and [PEAK Indicator] to the Display Timer settings. When the display goes dark, the [REC Indicator] and [PEAK Indicator] are also turned off.	NORMAL (indicators remain on) Power Save (indicators turned off)

R-09 追加機能のお知らせ (Ver.1.20)

本製品のバージョンは 1.20 にアップグレードされています。
これに伴い、以下の機能が追加されています。


ファイルを修復する (Repair)

録音の最中に、過ってアダプターが抜けてしまったり、カードを抜いてしまうなどのアクシデントのために再生できなくなったファイルを修復する機能が追加されました。

R-09 は、そのようなファイルを認識すると、ファインダーに「Repair」メニューを表示します。

1. 【ファインダー画面】で曲を選びます。

[PLAY ボタン ▲] [STOP ボタン ▼] で曲を選び、[REC ボタン] を押します。




2. 「Repair」を選びます。

[PLAY ボタン ▲] [STOP ボタン ▼] で「Repair」を選び、[REC ボタン] を押します。

メモ

このメニューは、R-09 が壊れた曲を認識した場合にのみ表示されます。



3. [REC ボタン] を押してファイルを修復します。

確認の画面が表示されます。[REC ボタン] を押して確定します。



メモ

中止 (キャンセル) する場合は、[REC ボタン] を押す前に [FINDER/MENU ボタン] を押してください。



ご注意!

修復中に電源を切らないでください。

4. 【基本画面】に戻します。

[FINDER/MENU ボタン] を押します。



ご注意!

修復しても、ファイルの末尾が最大 5 秒程度切り捨てられる場合があります。また、この機能によって、すべてのファイルが修復できるわけではありません。R-09 の使用中に、電源を切ったり、メモリー・カードを抜いたりしないでください。

各種設定の追加

【メニュー画面】に以下のパラメーターが新しく追加になりました。

カテゴリ	メニュー/効果	値 (初期値: 太字)
Recorder Setup	Max File Size 録音すると生成されるファイルのファイル・サイズの上限を設定します。MP3 で長時間録音したときに、WAV 変換後のサイズが大きすぎて、ソフトウェアによっては読み込めなくなるなどの問題を防ぐことができます。録音中の曲が設定された上限のサイズに達すると、R-09 は一旦そのファイルを閉じ、新たなファイルに録音を続けます。	64MB/128MB/256MB/512MB/ 1GB/2GB
	Peak Hold Level Meter のピーク・ホールドの設定します。ピーク・ホールドを ON にすると、入力信号中のもっとも大きい値を一定間ホールド (保持) して表示します。	OFF (ピーク・ホールドしない) / ON (ピーク・ホールドする)
Display Setup	Rec/Peak LED Display Timer の設定に連動して、ディスプレイが暗くなると同時に [REC インジケータ] および [PEAK インジケータ] を消灯させます。	NORMAL (インジケータを点灯する) / Power Save (インジケータを消灯する)